

Freecom FX-10 DVD+RW/+R



Meet the next generation of Freecom DVD Recorders

Freecom FX-10 DVD+RW/+R 4 USB-2

- Extremely fast and well designed DVD+RW/+R Recorder.
- Second generation DVD+RW drive that now write to DVD+R recordable disc as well.
- Compile, save and share your movies, music, data and photos.
- Great for DVD movies, MP3, Video CDs, backups and images.
- Installs in seconds without opening your computer.
- Connects and disconnects without restarting!
- Compatible with Windows 98SE/2000/ME/XP.
- Buffer under run prevention and Active Write Control (AWC).
- Unlimited free helpdesk support.
- Two years manufacturers warranty.
- Features a comprehensive software suite, media etc. for the best possible price.

What is DVD recording?

DVD recording is an evolution of rewritable CD technology and an extension to the DVD Video and DVD-ROM technology and offers you the ability to create custom DVDs. The recordable DVD format is designed for beginners and experts to record video, photos and data on a DVD disc. Rewritable DVD has tremendous appeal, caused by the growing popularity of multimedia applications and the need to record, store and share large amounts of data or video. Start burning your CDs and DVDs right away with the included software suite and media. Create, save and share your music, Video CDs, data and photo CDs. It's great for saving MP3, DVD movies, Video CDs, backup and image files. This Hi-Speed external USB-2 drive connects to your PC via the USB-2 port and can be installed and working within seconds without opening your computer. Two years manufacturers warranty. Free helpdesk support. The future is simple!



WWW.FREECOM.COM

Freecom
THE FUTURE IS SIMPLE!

Freecom FX-10 DVD+RW/+R

Product specifications	4x DVD+R, 2,4 DVD+RW, 12x DVD (read), 16x CD-R (write) 10x CD-RW (rewrite) 40x CD-ROM (read)	
Tray type	Electrical load / eject, horizontal auto tray	
Reading modes	DVD+R, DVD+RW, DVD-Video, DVD-ROM, Digital-Audio (Red book) and CD extra, CD-ROM (Mode 1 -Yellow book), CD-ROM XA & CD-I (Mode 2/Form 1-Green book), CD-ROM XA & CD-I (Mode 2/Form 2 -Green book), CD-Bridge & Photo-CD (single and multi-session), CD-Video	
Supported media	DVD+RW, DVD+R, CD-R, CD-RW, High Speed CD-RW, Mini-CD, Mini-DVD+RW (8 cm)	
Sequential Write	CD-R/RW: Disc At Once, Session At Once, Track At Once, Multi-Session, Packet Write (can not record DVD-R, DVD-RW and DVD-RAM media).	
Writing modes:	DVD+RW: Random Access Write, Sequential Write DVD+R: Sequential Write CD-R/CD-RW: Disc At Once, Session At once, Track At Once, Multi-Session, Packet Write	
Writing formats	DVD+RW/DVD+R: DVD-ROM, DVD-Video CD: CD-DA, CD-ROM, CD-ROM XA, CD Extra, MP3 CDs*, CD-I*, Mixed-ModeCD, VideoCD, PhotoCD*, CD TEXT, Bootable CD	
Interface	USB 2.0	
MTBF	50.000 hours (Duty 20%)	
Safety standards	Application Standard Radio Interference	UL1950 CSA950 EN60950 HHS Class1 EN60825-1 Class1 EN55022 EN61000-3-2 EN61000-3-3 ENN50082-1
Physical specifications	Height 5,1 - 7,5 cm x Width 17,1 cm x Length 25,8 cm - Weight 1,6 Kg	
Environmental specifications	Operating temp. Gradient Humidity Gradient	+5° to +50° C 20 °C /hour (max.) 5 - 80 % (No Condensation) 10 %/hour (max.)
Package includes:	<ul style="list-style-type: none"> • FX-10 external USB-2 DVD+RW/+R drive with Active Write Control • USB cable • Roxio EasyCD Creator recording software for PC & Toast for Mac. • Cyberlink Power DVD MPEG-2 decoding software (windows 98/2000/ME/XP) • Video edit & DVD authoring software (for PC only) • Media (1x DVD+RW, 1x CD-R/80 min.) • AC Adapter • Manual in 14 languages (UK, D, NL, F, I, E, TR, P, H, DK, S, N, PL, G) • Free help desk support • Two years manufacturers warranty 	
Power requirements	Voltage Adapter	+12V±8%, 1,5 A, automatic power ON-OFF function
System requirements	Pentium III, Celeron 700 MHz or higher, 128 MB RAM, 400 MB of free hard disk space, Windows 98SE/2000/ME/XP, available USB interface (USB 2.0 or USB 1.1), CD-ROM drive or internet connection (for driver / manual installation). Apple Mac G4 with OS X, v. 10.1 or higher and 128 MB RAM. For maximum performance of the FX-10 both computer system and software must support Hi-Speed USB-2	

* Included software does not support this feature.

	Freecom FX-10 4x USB-2	Freecom FA-1 USB-2PCI Card
Art. No. EU/UK	20111/20112	17789
EAN Code EU	4021801201119	4021801177896
EAN Code UK	4021801201126	



WWW.FREECOM.COM

Freecom
THE FUTURE IS SIMPLE!

ref. MM/FG/31-01-2003